

LM6121/LM6221/LM6321 High Speed Buffer

Check for Samples: [LM6121](#), [LM6221](#), [LM6321](#)

FEATURES

- High slew rate: 800 V/ μ s
- Wide bandwidth: 50 MHz
- Slew rate and bandwidth 100% tested
- Peak output current: ± 300 mA
- High input impedance: 5 M Ω
- LH0002H pin compatible
- No oscillations with capacitive loads

- 5V to ± 15 V operation guaranteed
- Current and thermal limiting
- Fully specified to drive 50 Ω lines

APPLICATIONS


- Line Driving
- Radar
- Sonar

DESCRIPTION

These high speed unity gain buffers slew at 800 V/ μ s and have a small signal bandwidth of 50 MHz while driving a 50 Ω load. They can drive ± 300 mA peak and do not oscillate while driving large capacitive loads. The LM6121 family are monolithic ICs which offer performance similar to the LH0002 with the additional features of current limit and thermal shutdown.

These buffers are built with National's VIP™ (Vertically Integrated PNP) process which provides fast PNP transistors that are true complements to the already fast NPN devices. This advanced junction-isolated process delivers high speed performance without the need for complex and expensive dielectric isolation.

Simplified Schematic



Numbers in () are for 8-pin N DIP.




Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

VIP is a trademark of Texas Instruments.


All other trademarks are the property of their respective owners.

Connection Diagram




*Heat-sinking pins. See Application section on heat sinking requirements.

Figure 1. Plastic DIP



Note: Pin 6 connected to case.

Figure 2. Metal Can - Top View C



*Pin 3 must be connected to the negative supply.

**Heat-sinking pins. See Application section on heat-sinking requirements. These pins are at V^- potential.

Figure 3. Plastic SOIC



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

Absolute Maximum Ratings ⁽¹⁾

Supply Voltage	36V (±18)
Input to Output Voltage ⁽²⁾	±7V
Input Voltage	±V _{supply}
Output Short-Circuit to GND	Continuous
⁽³⁾	
Storage Temperature Range	–65°C to +150°C
Lead Temperature	
(Soldering, 10 seconds)	260°C
Power Dissipation	⁽⁴⁾
ESD Tolerance ⁽⁵⁾	±2000V
Junction Temperature (T _{J(MAX)})	+150°C

- (1) Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications do not apply when operating the device beyond its rated operating conditions.
- (2) During current limit or thermal limit, the input current will increase if the input to output differential voltage exceeds 8V. For input to output differential voltages in excess of 8V the input current should be limited to ±20 mA.
- (3) The LM6121 series buffers contain current limit and thermal shutdown to protect against fault conditions.
- (4) The maximum power dissipation is a function of T_{J(max)}, θ_{JA}, and T_A. The maximum allowable power dissipation at any ambient temperature is $P_D = (T_{J(max)} - T_A) / \theta_{JA}$.
- (5) The test circuit consists of the human body model of 120 pF in series with 1500Ω.

Operating Ratings

Operating Temperature Range	
LM6121H/883	–55°C to +125°C
LM6221	–40°C to +85°C
LM6321	0°C to +70°C
Operating Supply Range	4.75 to ±16V
Thermal Resistance (θ _{JA}), ⁽¹⁾	
H Package	150°C/W
N Package	47°C/W
M Package	69°C/W
Thermal Resistance (θ _{JC}), H Package	17°C/W

- (1) The thermal resistance θ_{JA} of the device in the N package is measured when soldered directly to a printed circuit board, and the heat-sinking pins (pins 1, 4, 5 and 8) are connected to 2 square inches of 2 oz. copper. When installed in a socket, the thermal resistance θ_{JA} of the N package is 84°C/W. The thermal resistance θ_{JA} of the device in the M package is measured when soldered directly to a printed circuit board, and the heat-sinking pins (pins 1, 2, 6, 7, 8, 9, 13, 14) are connected to 1 square inch of 2 oz. copper.

DC Electrical Characteristics

The following specifications apply for Supply Voltage = $\pm 15V$, $V_{CM} = 0$, $R_L \geq 100\text{ k}\Omega$ and $R_S = 50\Omega$ unless otherwise noted.

Boldface limits apply for $T_A = T_J = T_{MIN}$ to T_{MAX} ; all other limits $T_A = T_J = 25^\circ\text{C}$.

Symbol	Parameter	Conditions	Typ	LM6121	LM6221	LM6321	Units
				Limit	Limit	Limit	
				(1) (2)	(1)	(1)	
A_{V1}	Voltage Gain 1	$R_L = 1\text{ k}\Omega$, $V_{IN} = \pm 10V$	0.990	0.980	0.980	0.970	
				0.970	0.950	0.950	
A_{V2}	Voltage Gain 2	$R_L = 50\Omega$, $V_{IN} = \pm 10V$	0.900	0.860	0.860	0.850	V/V
				0.800	0.820	0.820	Min
A_{V3}	Voltage Gain 3	$R_L = 50\Omega$, $V^+ = 5V$	0.840	0.780	0.780	0.750	
	(3)	$V_{IN} = 2 V_{PP}$ (1.5 V_{PP})		0.750	0.700	0.700	
V_{OS}	Offset Voltage	$R_L = 1\text{ k}\Omega$	15	30	30	50	mV
				50	60	100	Max
I_B	Input Bias Current	$R_L = 1\text{ k}\Omega$, $R_S = 10\text{ k}\Omega$	1	4	4	5	μA
				7	7	7	Max
R_{IN}	Input Resistance	$R_L = 50\Omega$	5				M Ω
C_{IN}	Input Capacitance		3.5				pF
R_O	Output Resistance	$I_{OUT} = \pm 10\text{ mA}$	3	5	5	5	Ω
				10	10	6	Max
I_{S1}	Supply Current 1	$R_L = \infty$	15	18	18	20	mA Max
				20	20	22	
I_{S2}	Supply Current 2	$R_L = \infty$, $V^+ = 5V$	14	16	16	18	
				18	18	20	
V_{O1}	Output Swing 1	$R_L = 1\text{ k}\Omega$	13.5	13.3	13.3	13.2	
				13	13	13	
V_{O2}	Output Swing 2	$R_L = 100\Omega$	12.7	11.5	11.5	11	$\pm V$
				10	10	10	Min
V_{O3}	Output Swing 3	$R_L = 50\Omega$	12	11	11	10	
				9	9	9	
V_{O4}	Output Swing 4	$R_L = 50\Omega$, $V^+ = 5V$	1.8	1.6	1.6	1.6	V_{PP}
		(3)		1.3	1.4	1.5	Min
PSSR	Power Supply	$V^\pm = \pm 5V$ to $\pm 15V$	70	60	60	60	dB
	Rejection Ratio			55	50	50	Min

(1) Limits are guaranteed by testing or correlation.

(2) For specification limits over the full Military Temperature Range, see RETS6121X.

(3) The input is biased to 2.5V and V_{IN} swings V_{PP} about this value. The input swing is $2 V_{PP}$ at all temperatures except for the A_V 3 test at -55°C where it is reduced to $1.5 V_{PP}$.

AC Electrical Characteristics

The following specifications apply for Supply Voltage = $\pm 15V$, $V_{CM} = 0$, $R_L \geq 100\text{ k}\Omega$ and $R_S = 50\Omega$ unless otherwise noted.

Boldface limits apply for $T_A = T_J = T_{MIN}$ to T_{MAX} ; all other limits $T_A = T_J = 25^\circ\text{C}$.

Symbol	Parameter	Conditions	Typ	LM6121	LM6221	LM6321	Units
				Limit (1)	Limit (1)	Limit (1)	
SR ₁	Slew Rate 1	$V_{IN} = \pm 11V$, $R_L = 1\text{ k}\Omega$	1200	550	550	550	V/ μ s Min
SR ₂	Slew Rate 2	$V_{IN} = \pm 11V$, $R_L = 50\Omega$	800	550	550	550	
		(2)					
SR ₃	Slew Rate 3	$V_{IN} = 2 V_{PP}$, $R_L = 50\Omega$ $V^+ = 5V$ (3)	50	550	550	550	
BW	-3 dB Bandwidth	$V_{IN} = \pm 100\text{ mV}_{PP}$, $R_L = 50\Omega$ $C_L \leq 10\text{ pF}$	50	30	30	30	MHz Min
t _r , t _f	Rise Time	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$	7.0				ns
	Fall Time	$V_O = 100\text{ mV}_{PP}$					
t _{pd}	Propagation	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$	4.0				ns
	Delay Time	$V_O = 100\text{ mV}_{PP}$					
O _S	Overshoot	$R_L = 50\Omega$, $C_L \leq 10\text{ pF}$ $V_O = 100\text{ mV}_{PP}$	10				%











(1) Limits are guaranteed by testing or correlation.

(2) Slew rate is measured with a $\pm 11V$ input pulse and 50Ω source impedance at 25°C . Since voltage gain is typically 0.9 driving a 50Ω load, the output swing will be approximately $\pm 10V$. Slew rate is calculated for transitions between $\pm 5V$ levels on both rising and falling edges. A high speed measurement is done to minimize device heating. For slew rate versus junction temperature see typical performance curves. The input pulse amplitude should be reduced to $\pm 10V$ for measurements at temperature extremes. For accurate measurements, the input slew rate should be at least $1700\text{ V}/\mu\text{s}$.

(3) The input is biased to $2.5V$ and V_{IN} swings V_{PP} about this value. The input swing is $2 V_{PP}$ at all temperatures except for the $A_V 3$ test at -55°C where it is reduced to $1.5 V_{PP}$.


Typical Performance Characteristics

T_J = 25°C, unless otherwise specified



Typical Performance Characteristics (continued)

$T_J = 25^\circ\text{C}$, unless otherwise specified



Application Hints

POWER SUPPLY DECOUPLING

The method of supply bypassing is not critical for stability of the LM6121 series buffers. However, their high current output combined with high slew rate can result in significant voltage transients on the power supply lines if much inductance is present. For example, a slew rate of $900\text{ V}/\mu\text{s}$ into a 50Ω load produces a di/dt of $18\text{ A}/\mu\text{s}$. Multiplying this by a wiring inductance of 50 nH (which corresponds to approximately $1\frac{1}{2}$ " of 22 gauge wire) result in a 0.9V transient. To minimize this problem use high quality decoupling very close to the device. Suggested values are a $0.1\ \mu\text{F}$ ceramic in parallel with one or two $2.2\ \mu\text{F}$ tantalums. A ground plane is recommended.

LOAD IMPEDANCE

The LM6121 is stable to any load when driven by a 50Ω source. As shown in the *Overshoot vs Capacitive Load* graph, worst case is a purely capacitive load of about 1000 pF . Shunting the load capacitance with a resistor will reduce overshoot.

SOURCE INDUCTANCE

Like any high frequency buffer, the LM6121 can oscillate at high values of source inductance. The worst case condition occurs at a purely capacitive load of 50 pF where up to 100 nH of source inductance can be tolerated. With a 50Ω load, this goes up to 200 nH . This sensitivity may be reduced at the expense of a slight reduction in bandwidth by adding a resistor in series with the buffer input. A 100Ω resistor will ensure stability with source inductances up to 400 nH with any load.

OVERVOLTAGE PROTECTION

The LM6121 may be severely damaged or destroyed if the Absolute Maximum Rating of 7V between input and output pins is exceeded.

If the buffer's input-to-output differential voltage is allowed to exceed 7V, a base-emitter junction will be in reverse-breakdown, and will be in series with a forward-biased base-emitter junction. Referring to the LM6121 simplified schematic, the transistors involved are Q1 and Q3 for positive inputs, and Q2 and Q4 for negative inputs. If any current is allowed to flow through these junctions, localized heating of the reverse-biased junction will occur, potentially causing damage. The effect of the damage is typically increased offset voltage, increased bias current, and/or degraded AC performance. Furthermore, this will defeat the short-circuit and over-temperature protection circuitry. Exceeding $\pm 7V$ input with a shorted output will destroy the device.

The device is best protected by the insertion of the parallel combination of a 100 k Ω resistor (R1) and a small capacitor (C1) in series with the buffer input, and a 100 k Ω resistor (R2) from input to output of the buffer (see Figure 4). This network normally has no effect on the buffer output. However, if the buffer's current limit or shutdown is activated, and the output has a ground-referred load of significantly less than 100 k Ω , a large input-to-output voltage may be present. R1 and R2 then form a voltage divider, keeping the input-output differential below the 7V Maximum Rating for input voltages up to 14V. This protection network should be sufficient to protect the LM6121 from the output of nearly any op amp which is operated on supply voltages of $\pm 15V$ or lower.




Figure 4. LM6121 with Overvoltage Protection

HEATSINK REQUIREMENTS

A heatsink may be required with the LM6321 depending on the maximum power dissipation and maximum ambient temperature of the application. Under all possible operating conditions, the junction temperature must be within the range specified under Absolute Maximum Ratings.

To determine if a heatsink is required, the maximum power dissipated by the buffer, $P(\max)$, must be calculated. The formula for calculating the maximum allowable power dissipation in any application is $P_D = (T_J(\max) - T_A) / \theta_{JA}$. For the simple case of a buffer driving a resistive load as in Figure 5, the maximum DC power dissipation occurs when the output is at half the supply. Assuming equal supplies, the formula is $P_D = I_S (2V^+) + V^{+2} / 4 R_L$.




Figure 5.

The next parameter which must be calculated is the maximum allowable temperature rise, $T_R(\max)$. This is calculated by using the formula:

$$T_R(\max) = T_J(\max) - T_A(\max) \quad (1)$$

where: $T_J(\max)$ is the maximum allowable junction temperature

$T_A(\max)$ is the maximum ambient temperature

Using the calculated values for $T_R(\max)$ and $P(\max)$, the required value for junction-to-ambient thermal resistance, $\theta_{(J-A)}$, can now be found:

$$\theta_{(J-A)} = T_R(\max) / P(\max) \quad (2)$$

The heatsink for the LM6321 is made using the PC board copper. The heat is conducted from the die, through the lead frame (inside the part), and out the pins which are soldered to the PC board. The pins used for heat conduction are:

Part	Package	Pins
LM6321N	8-Pin DIP	1, 4, 5, 8
LM6321M	14-Pin SO	1, 2, 3, 6, 7, 8, 9, 13, 14

Figure 8 shows copper patterns which may be used to dissipate heat from the LM6321.

Figure 6. 8-Pin DIP





Figure 7. 14-Pin SOIC, Copper Heatsink Patterns



*For best results, use $L = 2H$

Figure 8.

Table 1.

Package	L (in.)	H (in.)	θ_{JA} ($^{\circ}C/W$)
8-Pin DIP	2	0.5	47
14-Pin SO	1	0.5	69
	2	1	57

Table 1 shows some values of junction-to-ambient thermal resistance (θ_{JA}) for values of L and W for 2 oz. copper:

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components which meet ISO/TS16949 requirements, mainly for automotive use. Components which have not been so designated are neither designed nor intended for automotive use; and TI will not be responsible for any failure of such components to meet such requirements.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com