


LM2902, LM324/LM324A, LM224/ LM224A Quad Operational Amplifier

Features


- Internally frequency compensated for unity gain
- Large DC voltage gain: 100dB
- Wide power supply range:
LM224/LM224A, LM324/LM324A : 3V~32V (or $\pm 1.5 \sim 15V$)
LM2902: 3V~26V (or $\pm 1.5V \sim 13V$)
- Input common mode voltage range includes ground
- Large output voltage swing: 0V to VCC -1.5V
- Power drain suitable for battery operation

Description

The LM324/LM324A, LM2902, LM224/LM224A consist of four independent, high gain, internally frequency compensated operational amplifiers which were designed specifically to operate from a single power supply over a wide voltage range. Operation from split power supplies is also possible so long as the difference between the two supplies is 3 volts to 32 volts. Application areas include transducer amplifier, DC gain blocks and all the conventional OP amp circuits which now can be easily implemented in single power supply systems.




Internal Block Diagram



Schematic Diagram

(One Section Only)



Absolute Maximum Ratings

Parameter	Symbol	LM224/LM224A	LM324/LM324A	LM2902	Unit
Power Supply Voltage	V _{CC}	±16 or 32	±16 or 32	±13 or 26	V
Differential Input Voltage	V _{I(DIFF)}	32	32	26	V
Input Voltage	V _I	-0.3 to +32	-0.3 to +32	-0.3 to +26	V
Output Short Circuit to GND V _{CC} ≤15V, T _A =25°C(one Amp)	-	Continuous	Continuous	Continuous	-
Power Dissipation	P _D	570	570	570	mW
Operating Temperature Range	T _{OPR}	-25 ~ +85	0 ~ +70	-40 ~ +85	°C
Storage Temperature Range	T _{STG}	-65 ~ +150	-65 ~ +150	-65 ~ +150	°C

Electrical Characteristics

(V_{CC}=5.0V, V_{EE}=GND, T_A=25 °C, unless otherwise specified)

Parameter	Symbol	Conditions	LM224			LM324			LM2902			Unit
			Min.	Typ.	Max.	Min.	Typ.	Max.	Min.	Typ.	Max.	
Input Offset Voltage	V _{IO}	V _{CM} = 0V to V _{CC} -1.5V V _{O(P)} = 1.4V, R _S = 0Ω	-	1.5	5.0	-	1.5	7.0	-	1.5	7.0	mV
Input Offset Current	I _{IO}	-	-	2.0	30	-	3.0	50	-	3.0	50	nA
Input Bias Current	I _{IBIAS}	-	-	40	150	-	40	250	-	40	250	nA
Common-Mode Input Voltage Range	V _{I(R)}	Note1	0	-	V _{CC} -1.5	0	V _{CC} -1.5	-	0	-	V _{CC} -1.5	V
Supply Current	I _{CC}	RL = ∞, V _{CC} = 30V (all Amps)	-	1.0	3	-	1.0	3	-	1.0	3	mA
		RL = ∞, V _{CC} = 5V (all Amps) (V _{CC} = 26V for LM2902)	-	0.7	1.2	-	0.7	1.2	-	0.7	1.2	mA
Large Signal Voltage Gain	G _V	V _{CC} = 15V, R _L ≥ 2KΩ V _{O(P)} = 1V to 11V	50	100	-	25	100	-	-	100	-	V/ mV
Output Voltage Swing	V _{O(H)}	Note1	RL = 2KΩ	26	-	-	26	-	-	22	-	-
			RL = 10KΩ	27	28	-	27	28	-	23	24	-
	V _{O(L)}	V _{CC} = 5V, R _L ≥ 10KΩ	-	5	20	-	5	20	-	5	100	mV
Common-Mode Rejection Ratio	CMRR	-	70	85	-	65	75	-	50	75	-	dB
Power Supply Rejection Ratio	PSRR	-	65	100	-	65	100	-	50	100	-	dB
Channel Separation	CS	f = 1KHz to 20Khz	-	120	-	-	120	-	-	120	-	dB
Short Circuit to GND	I _{SC}	-	-	40	60	-	40	60	-	40	60	mA
Output Current	I _{SOURCE}	V _{I(+)} = 1V, V _{I(-)} = 0V V _{CC} = 15V, V _{O(P)} = 2V	20	40	-	20	40	-	20	40	-	mA
	I _{SINK}	V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V, V _{O(P)} = 2V	10	13	-	10	13	-	10	13	-	mA
		V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V, V _{O(R)} = 200mV	12	45	-	12	45	-	-	-	-	μA
Differential Input Voltage	V _{I(DIFF)}		-	-	V _{CC}	-	-	V _{CC}	-	-	V _{CC}	V

Note :

1. V_{CC}=30V for LM224 and LM324 , V_{CC} = 26V for LM2902

Electrical Characteristics

(V_{CC} = 5.0V, V_{EE} = GND, unless otherwise specified)

The following specification apply over the range of -25 °C ≤ T_A ≤ +85 °C for the LM224; and the 0 °C ≤ T_A ≤ +70 °C for the LM324 ; and the -40°C ≤ T_A ≤ +85 °C for the LM2902

Parameter	Symbol	Conditions	LM224			LM324			LM2902			Unit	
			Min.	Typ.	Max.	Min.	Typ.	Max.	Min.	Typ.	Max.		
Input Offset Voltage	V _{IO}	V _{ICM} = 0V to V _{CC} -1.5V V _{O(P)} = 1.4V, R _S = 0Ω	-	-	7.0	-	-	9.0	-	-	10.0	mV	
Input Offset Voltage Drift	ΔV _{IO} /ΔT	-	-	7.0	-	-	7.0	-	-	7.0	-	μV/ °C	
Input Offset Current	I _{IO}	-	-	-	100	-	-	150	-	-	200	nA	
Input Offset Current Drift	ΔI _{IO} /ΔT	-	-	10	-	-	10	-	-	10	-	pA/ °C	
Input Bias Current	I _{BIAS}	-	-	-	300	-	-	500	-	-	500	nA	
Common-Mode Input Voltage Range	V _{I(R)}	Note1	0	-	V _{CC} -2.0	0	-	V _{CC} -2.0	0	-	V _{CC} -2.0	V	
Large Signal Voltage Gain	G _V	V _{CC} = 15V, R _L ≥ 2.0KΩ V _{O(P)} = 1V to 11V	25	-	-	15	-	-	15	-	-	V/mV	
Output Voltage Swing	V _{O(H)}	Note1	RL = 2KΩ	26	-	-	26	-	-	22	-	-	V
			RL = 10KΩ	27	28	-	27	28	-	23	24	-	V
	V _{O(L)}	V _{CC} = 5V, R _L ≥ 10KΩ		5	20	-	5	20	-	5	100	mV	
Output Current	I _{SOURCE}	V _{I(+)} = 1V, V _{I(-)} = 0V V _{CC} = 15V, V _{O(P)} = 2V	10	20	-	10	20	-	10	20	-	mA	
	I _{SINK}	V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V, V _{O(P)} = 2V	10	13	-	5	8	-	5	8	-	mA	
Differential Input Voltage	V _{I(DIFF)}	-	-	-	V _{CC}	-	-	V _{CC}	-	-	V _{CC}	V	

Note:

1. V_{CC}=30V for LM224 and LM324 , V_{CC} = 26V for LM2902

Electrical Characteristics

(V_{CC}=5.0V, V_{EE} = GND, T_A=25 °C, unless otherwise specified)

Parameter	Symbol	Conditions	LM224A			LM324A			Unit
			Min.	Typ.	Max.	Min.	Typ.	Max.	
Input Offset Voltage	V _{IO}	V _{CM} = 0V to V _{CC} -1.5V V _{O(P)} = 1.4V, R _S = 0 Ω	-	1.0	3.0	-	1.5	3.0	mV
Input Offset Current	I _{IO}	-	-	2	15	-	3.0	30	nA
Input Bias Current	I _{BIAS}	-	-	40	80	-	40	100	nA
Input Common-Mode Voltage Range	V _{I(R)}	V _{CC} = 30V	0	-	V _{CC} -1.5	0	-	V _{CC} -1.5	V
Supply Current (All Amps)	I _{CC}	V _{CC} = 30V	-	1.5	3	-	1.5	3	mA
		V _{CC} = 5V	-	0.7	1.2	-	0.7	1.2	mA
Large Signal Voltage Gain	G _V	V _{CC} = 15V, R _L ≥ 2 KΩ V _{O(P)} = 1V to 11V	50	100	-	25	100	-	V/mV
Output Voltage Swing	V _{O(H)}	Note1	R _L = 2 KΩ	26	-	-	26	-	-
			R _L = 10 KΩ	27	28	-	27	28	-
	V _{O(L)}	V _{CC} = 5V, R _L ≥ 10 KΩ	-	5	20	-	5	20	mV
Common-Mode Rejection Ratio	CMRR	-	70	85	-	65	85	-	dB
Power Supply Rejection Ratio	PSRR	-	65	100	-	65	100	-	dB
Channel Separation	CS	f = 1KHz to 20Khz	-	120	-	-	120	-	dB
Short Circuit to GND	I _{SC}	-	-	40	60	-	40	60	mA
Output Current	I _{SOURCE}	V _{I(+)} = 1V, V _{I(-)} = 0V V _{CC} = 15V	20	40	-	20	40	-	mA
	I _{SINK}	V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V, V _{O(P)} = 2V	10	20	-	10	20	-	mA
		V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V, V _{O(P)} = 200mV	12	50	-	12	50	-	μA
Differential Input Voltage	V _{I(DIFF)}	-	-	-	V _{CC}	-	-	V _{CC}	V

Note:

1. V_{CC}=30V for LM224A, LM324A

Electrical Characteristics

(V_{CC} = 5.0V, V_{EE} = GND, unless otherwise specified)

The following specification apply over the range of -25°C ≤ T_A ≤ + 85 °C for the LM224A; and the 0 °C ≤ T_A ≤+70 °C for the LM324A

Parameter	Symbol	Conditions	LM224A			LM324A			Unit
			Min.	Typ.	Max.	Min.	Typ.	Max.	
Input Offset Voltage	V _{IO}	V _{CM} = 0V to V _{CC} -1.5V V _{O(P)} = 1.4V, R _S = 0Ω	-	-	4.0	-	-	5.0	mV
Input Offset Voltage Drift	ΔV _{IO} /ΔT	-	-	7.0	20	-	7.0	30	μV/ °C
Input Offset Current	I _{IO}	-	-	-	30	-	-	75	nA
Input Offset Current Drift	ΔI _{IO} /ΔT	-	-	10	200	-	10	300	pA/ °C
Input Bias Current	I _{BIAS}	-	-	40	100	-	40	200	nA
Common-Mode Input Voltage Range	V _{I(R)}	V _{CC} = 30V	0	-	V _{CC} -2.0	0	-	V _{CC} -2.0	V
Large Signal Voltage Gain	G _V	V _{CC} = 15V, R _L ≥ 2.0KΩ	25	-	-	15	-	-	V/mV
Output Voltage Swing	V _{O(H)}	V _{CC} = 30V	26	-	-	26	-	-	V
		R _L = 2KΩ	27	28	-	27	28	-	
Output Current	V _{O(L)}	V _{CC} = 5V, R _L ≥ 10KΩ	-	5	20	-	5	20	mA
	I _{SOURCE}	V _{I(+)} = 1V, V _{I(-)} = 0V V _{CC} = 15V	10	20	-	10	20	-	mA
	I _{SINK}	V _{I(+)} = 0V, V _{I(-)} = 1V V _{CC} = 15V	5	8	-	5	8	-	mA
	V _{I(DIFF)}	-	-	-	V _{CC}	-	-	V _{CC}	V

Typical Performance Characteristics




Figure 1. Input Voltage Range vs Supply Voltage




Figure 2. Input Current vs Temperature




Figure 3. Supply Current vs Supply Voltage




Figure 4. Voltage Gain vs Supply Voltage




Figure 5. Open Loop Frequency Response




Figure 6. Common mode Rejection Ratio

Typical Performance Characteristics (continued)




Figure 7. Slew Rate




Figure 8. Voltage Follower Pulse Response




Figure 9. Large Signal Frequency Response




Figure 10. Output Characteristics vs Current Sourcing




Figure 11. Output Characteristics vs Current Sinking





Figure 12. Current Limiting vs Temperature

Mechanical Dimensions


Package



Mechanical Dimensions (Continued)

Package

14-SOP



Ordering Information

Product Number	Package	Operating Temperature
LM324N	14-DIP	0 ~ + 70 °C
LM324AN		
LM324M	14-SOP	-40 ~ + 85 °C
LM324AM		
LM2902N	14-DIP	-25 ~ +85 °C
LM2902M	14-SOP	
LM224N	14-DIP	
LM224AN		
LM224M	14-SOP	
LM224AM		

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.