

Data Sheet July 2001 FN4561.6

# Radiation Hardened High-Speed, Dual Output PWM

The Radiation Hardened HS-1825ARH Pulse Width Modulator is designed to be used in high frequency switched-mode power supplies and can be used in either current-mode or voltage-mode. It is well suited for single-ended boost converter applications.

Device features include a precision voltage reference, low power start-up circuit, high frequency oscillator, wide-band error amplifier, and fast current-limit comparator. The use of proprietary process capabilities and unique design techniques results in fast propagation delay times and high output current over a wide range of output voltages.

Constructed with the Intersil Rad Hard Silicon Gate (RSG) Dielectric Isolation BiCMOS process, the HS-1825ARH has been specifically designed to provide highly reliable performance when exposed to harsh radiation environments.

Specifications for Rad Hard QML devices are controlled by the Defense Supply Center in Columbus (DSCC). The SMD numbers listed below must be used when ordering.

Detailed Electrical Specifications for the HS-1825ARH are contained in SMD 5962-99558. That document may be easily downloaded from our website.

www.intersil.com/

# Ordering Information

ORDERING NUMBER	INTERSIL MKT. NUMBER	TEMP. RANGE (°C)
5962F9955801VEC	HS1-1825ARH-Q	-50 to 125
5962F9955801QEC	HS1-1825ARH-8	-50 to 125
5962F9955801VXC	HS9-1825ARH-Q	-50 to 125
5962F9955801QXC	HS9-1825ARH-8	-50 to 125
HS1-1825ARH/Proto	HS1-1825ARH/Proto	-50 to 125
HS9-1825ARH/Proto	HS9-1825ARH/Proto	-50 to 125

#### Features


- Electrically Screened to DESC SMD # 5962-99558
- · QML Qualified per MIL-PRF-38535 Requirements
- · Radiation Environment
  - Maximum Total Dose . . . . . . . . . . . . 300 krad(SI)
  - Vertical Architecture Provides Low Dose Rate Immunity
  - DI RSG Process Provides Latch-Up Immunity
- Fast Propagation Delay . . . . . . . . . . 80ns (Typ)
- · 12V to 30V Operation
- · 1A (Peak) Dual Output Drive Capability
- 5.1V Reference
- · Under-Voltage Lockout
- · Programmable Soft-Start
- · Switching Frequencies to 500kHz
- · Trimmed Oscillator Discharge Current
- Latched Overcurrent Comparator with Full Cycle Restart
- · Programmable Leading Edge Blanking Circuit

## **Applications**

- · Current or Voltage Mode Switching Power Supplies
- · Motor Speed and Direction Control

#### **Pinout**

#### HS-1825ARH SBDIP (CDIP2-T16) AND FLATPACK (CDFP4-F16) TOP VIEW



NOTE: Grounding the Soft Start pin does not inhibit the outputs. The outputs may be inhibited by applying >1.26V to the ILIM/SD pin.

### Die Characteristics

#### **DIE DIMENSIONS**

 $4710\mu m$  x  $3570\mu m$  (185 mils x 140 mils) Thickness:  $483\mu m$   $\pm 25.4\mu m$  (19 mils  $\pm 1$  mil)

#### **INTERFACE MATERIALS**

#### Glassivation

Type: PSG (Phosphorous Silicon Glass)

Thickness: 8.0kÅ ±1.0kÅ

# **Top Metallization**

Type: ALSiCu

Thickness: 16.0kÅ ±2kÅ

#### **Substrate**

Radiation Hardened Silicon Gate,

Dielectric Isolation

# Metallization Mask Layout

#### **Backside Finish**

Silicon

#### **ASSEMBLY RELATED INFORMATION**

#### Substrate Potential

Unbiased (DI)

#### **ADDITIONAL INFORMATION**


#### **Worst Case Current Density**

 $< 2.0 \times 10^5 \text{ A/cm}^2$ 

#### **Transistor Count**

225

#### HS-1825ARH



#### NOTES:

- This is the oscillator ground (OSCGND) bond pad and must be connected to GND.
- 2. PGND and VC each require two bond pad connections.

All Intersil U.S. products are manufactured, assembled and tested utilizing ISO9000 quality systems. Intersil Corporation's quality certifications can be viewed at www.intersil.com/design/quality

Intersil products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design, software and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.

For information regarding Intersil Corporation and its products, see www.intersil.com