

LM831

LM831 Low Voltage Audio Power Amplifier



Literature Number: SNOSBP6A

LM831 Low Voltage Audio Power Amplifier

General Description

The LM831 is a dual audio power amplifier optimized for very low voltage operation. The LM831 has two independent amplifiers, giving stereo or higher power bridge (BTL) operation from two- or three-cell power supplies.

The LM831 uses a patented compensation technique to reduce high-frequency radiation for optimum performance in AM radio applications. This compensation also results in lower distortion and less wide-band noise.

The input is direct-coupled to the LM831, eliminating the usual coupling capacitor. Voltage gain is adjustable with a single resistor.

Features


- Low voltage operation, 1.8V to 6.0V
- High power, 440 mW, 8Ω, BTL, 3V
- Low AM radiation
- Low noise
- Low THD

Applications

- Portable tape recorders
- Portable radios
- Headphone stereo
- Portable speakers

Typical Application

Dual Amplifier with Minimum Parts



TL/H/6754-1

$A_V = 46 \text{ dB}$, $BW = 250 \text{ Hz to } 35 \text{ kHz}$
 $P_{OUT} = 220 \text{ mW/Ch}$, $R_L = 4\Omega$

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

Supply Voltage, V_S	7.5V
Input Voltage, V_{IN}	$\pm 0.4V$
Power Dissipation (Note 1), P_D	1.3W (M Package) 1.4W (N Package)
Operating Temperature (Note 1), T_{opr}	$-40^{\circ}C$ to $+85^{\circ}C$

Storage Temperature, T_{stg}	$-65^{\circ}C$ to $+150^{\circ}C$
Junction Temperature, T_J	$+150^{\circ}C$
Lead Temp. (Soldering, 10 sec.), T_L	$+260^{\circ}C$
Thermal Resistance	
θ_{JC} (DIP)	$27^{\circ}C/W$
θ_{JA} (DIP)	$75^{\circ}C/W$
θ_{JC} (SO Package)	$20^{\circ}C/W$
θ_{JA} (SO Package)	$95^{\circ}C/W$


Electrical Characteristics

Unless otherwise specified, $T_A = 25^{\circ}C$, $V_S = 3V$, $f = 1$ kHz, test circuit is dual or BTL amplifier with minimum parts.

Symbol	Parameter	Conditions	Typ	Tested Limit	Unit (Limit)
V_S	Operating Voltage		3 3	1.8 6	V (Min) V (Max)
I_Q	Supply Current	$V_{IN} = 0$, Dual Mode $V_{IN} = 0$, BTL Mode	5 6	10 15	mA (Max) mA (Max)
V_{OS}	Output DC Offset	$V_{IN} = 0$, BTL Mode	10	50	mV (Max)
R_{IN}	Input Resistance		25	15 35	k (Min) k (Max)
A_V	Voltage Gain	$V_{IN} = 2.25$ mV _{rms} , $f = 1$ kHz, Dual Mode	46	44 48	dB (Min) dB (Max)
PSRR	Supply Rejection	$V_S = 3V + 200$ mV _{rms} @ $f = 1$ kHz	46	30	dB (Min)
P_{OD}	Power Out	$V_S = 3V$, $R_L = 4\Omega$, 10% THD, Dual Mode	220	150	mW (Min)
P_{ODL}	Power Out Low, V_S	$V_S = 1.8V$, $R_L = 4\Omega$, 10% THD, Dual Mode	45	10	mW (Min)
P_{OB}	Power Out	$V_S = 3V$, $R_L = 8\Omega$, 10% THD, BTL Mode	440	300	mW (Min)
P_{OBL}	Power Out Low, V_S	$V_S = 1.8V$, $R_L = 8\Omega$, 10% THD, BTL Mode	90	20	mW (Min)
Sep	Channel Separation	Referenced to $V_O = 200$ mV _{rms}	52	40	dB (Min)
I_B	Input Bias Current		1	2	μA (Max)
E_{n0}	Output Noise	Wide Band (250 ~ 35 kHz)	250	500	μV (Max)
THD	Distortion	$V_S = 3V$, $P_O = 50$ mW, $f = 1$ kHz, Dual	0.25	1	% (Max)

Note 1: For operation in ambient temperatures above $25^{\circ}C$, the device must be derated based on a $150^{\circ}C$ maximum junction temperature and a thermal resistance of $98^{\circ}C/W$ junction to ambient for the M package or $90^{\circ}C/W$ junction to ambient for the N package.







Connection Diagram



TL/H/6754-2







Order Number LM831M or N
See NS Package Number M16B or N16E

Typical Performance Characteristics









TL/H/6754-4

Typical Performance Characteristics (Continued)








TL/H/6754-5

Typical Performance Characteristics (Continued)



TL/H/6754-6

Typical Performance Characteristics (Continued)




Note 2: 1 kHz curve is measured with 400 Hz–30 kHz Filter.

TL/H/6754-7

Typical Applications


BTL Amplifier with Minimum Parts



TL/H/6754-8

$A_V = 52 \text{ dB}$, $BW = 250 \text{ Hz to } 25 \text{ kHz}$
 $P_{OUT} = 440 \text{ mW}$, $R_L = 8\Omega$

BTL Amplifier for Hi-Fi Quality




TL/H/6754-9

$A_V = 40 \text{ dB}$, $BW = 20 \text{ Hz to } 20 \text{ kHz}$
 $P_{OUT} = 440 \text{ mW}$, $R_L = 8\Omega$
 (Dynamic Range Over 80 dB)

Typical Applications (Continued)


Dual Amplifier for Hi-Fi Quality



TL/H/6754-10

$A_V = 34 \text{ dB}$, $BW = 50 \text{ Hz to } 20 \text{ kHz}$
 $P_{OUT} = 220 \text{ mW/Ch}$, $R_L = 4\Omega$
 (Dynamic Range Over 80 dB)

Low-Cost Power Amplifier (No Bootstrap)



TL/H/6754-11

$P_{OUT} = 150 \text{ mW/Ch}$, $BW = 300 \text{ Hz to } 35 \text{ kHz}$
 BTL Mode is also possible


*For 3-cell applications, the 120k resistor should be changed to 20K.

Feedback is provided to the input transistor Q_1 emitter by R_6 and R_7 .

R₅ is provided for bridge (BTL) operation.

TL/H/6754-12

LM831 Equivalent Schematic




External Components (Refer to External Component Diagram)

Component	Comments	Min	Max
C _O	Required to stabilize output stage.	0.33 μ F	1 μ F
C _c	Output coupling capacitors for Dual Mode. Sets a low-frequency pole in the frequency response. $f_L = \frac{1}{2\pi C_c R_L}$	100 μ F	10,000 μ F
C _{BS}	Bootstrap capacitors. Sets a low-frequency pole in the power BW. Recommended value is $C_{BS} = \frac{1}{10 \cdot 2\pi \cdot f_L \cdot R_L}$	22 μ F or (short Pins 4 & 12 to 9)	470 μ F
C _S	Supply bypass. Larger values improve low-battery performance by reducing supply ripple.	47 μ F	10,000 μ F
C _{BY}	Filters the supply for improved low-voltage operation. Also sets turn-on delay.	47 μ F	470 μ F
C _{NF}	Sets a low-frequency response. Also affects turn-on delay. $f_L = \frac{1}{2\pi \cdot C_{NF} \cdot (R_{AV} + 80)}$ In BTL Mode, C _{NF} on Pin 15 can be reduced without affecting the frequency response. However, the turn-on "POP" will be worsened.	10 μ F	100 μ F
C _{BTL}	Used only in the Bridge Mode. Connects the output of the first amplifier to the inverting input of the other through an internal resistor. Sets a low-frequency pole in one-half the frequency response. $f_L = \frac{1}{2\pi \cdot C_{BTL} \cdot 16k}$	0.1 μ F	1 μ F
C _{BW}	Improves clipping waveform and sets the high-frequency bandwidth. Works with an internal 16k resistor. (This equation applies for R _{AV} \neq 0. For 46 dB application, see BW–C _{BW} curve.) $f_H = \frac{1}{2\pi \cdot C_{BW} \cdot 16k}$	See table below	
R _{AV}	Used to reduce the gain and improve the distortion and signal to noise. If this is desired, C _{BW} must also be used.	See table below	

Typical A _v	R _{AV}	C _{BW}	
		Min	Max
46 dB	Short	Open	4700 pF
40 dB	82	100 pF	4700 pF
34 dB	240	270 pF	4700 pF
28 dB	560	500 pF	4700 pF


Printed Circuit Layout for LM831N (Foil Side View) Refer to External Component Diagram




TL/H/6754-14

Note: Power ground pattern should be as wide as possible. Supply bypass capacitor should be as close to the IC as possible. Output compensation capacitors should also be close to the IC.

Physical Dimensions inches (millimeters)



Molded SO Package (M)
Order Number LM831M
NS Package Number M16B

Physical Dimensions inches (millimeters) (Continued)**LIFE SUPPORT POLICY**

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



National Semiconductor Corporation
1111 West Bardin Road
Arlington, TX 76017
Tel: 1(800) 272-9959
Fax: 1(800) 737-7018

National Semiconductor Europe
Fax: (+49) 0-180-530 85 86
Email: onjwge@tevm2.nsc.com
Deutsch Tel: (+49) 0-180-530 85 85
English Tel: (+49) 0-180-532 78 32
Français Tel: (+49) 0-180-532 93 58
Italiano Tel: (+49) 0-180-534 16 80

National Semiconductor Hong Kong Ltd.
13th Floor, Straight Block,
Ocean Centre, 5 Canton Rd.
Tsimshatsui, Kowloon
Hong Kong
Tel: (852) 2737-1600
Fax: (852) 2736-9960

National Semiconductor Japan Ltd.
Tel: 81-043-299-2309
Fax: 81-043-299-2408

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Transportation and Automotive	www.ti.com/automotive
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated