

Low Cost Triple CRT Driver

CVA2422TL

FEATURES

•	Bandwidth	90MHz
•	Rise/Fall Time	5.0ns
•	Swing	70V P-P
	Supply Voltage	

APPLICATIONS

 CRT driver for up to 82kHz monitors with resolution up to 1280 x 1024.


DESCRIPTION

The CVA2422TL contains three cascode video driver amplifiers without a common emitter. This device is designed for ease of use, adjustable gain, controlled EMI, OSD, and external peaking.

The part is housed in the industry standard 11-lead TO-220 molded power package. The heat sink is floating and may be grounded for ease of manufacturing and RFI shielding.

ORDERING INFORMATION

Part	Package	Temperature
CVA2422TL	T11A	-20°C to +90°C



CVA2422TL



ABSOLUTE MAXIMUM RATINGS


Supply Voltage95V	Operating Temperature20°C to +90°C
Power Dissipation	Lead Temperature
Storage Temperature25°C to +100°C	

DC ELECTRICAL CHARACTERISTICS $V_s = 80V$, $C_L = 8pF$, $DC_{INPUT\ BIAS} = 12V$, $V_{IN} = 3.4V$, $V_{OUT} = 50V_{p-p}$. $T_{CASE} = +25^{\circ}C$. See Figure 1.


SYMBOL	CHARACTERISTICS	MIN	TYP	MAX	UNITS
Icc	Supply Current @ 1MHz		34	40	mA
Icc	Supply Current @ 50MHz		58		mA
Vout DC	Output DC Level	40	45	50	V
Av	Voltage Gain	12	15	17	V
	Gain Matching		0.2		dB


AC ELECTRICAL CHARACTERISTICS $V_s = 80V$, $C_L = 8pF$, $DC_{INPUT\,BIAS} = 12V$, $V_{IN} = 3.4V$, $V_{OUT} = 50V_{p-p}$. $T_{CASE} = +25^{\circ}C$. See Figure 1.

SYMBOL	CHARACTERISTICS	MIN	TYP	MAX	UNITS
Tr	Rise Time		5	6	ns
Tf	Fall Time		5	6	ns
BW	Bandwidth		90		MHz
Le	Linearity		6		%
OS	Overshoot		6		%









CVA2422TL



APPLICATION INFORMATION

The CVA2422TL is a high voltage triple CRT driver suitable for VGA, Super VGA, IBM® 8514, 1280 x 1024 and 1024 x 768 non-interlaced display applications. The CVA2422TL features 80V operation. The part is housed in the industry standard 11 lead TO-220 molded power package. The heat sink is floating and may be grounded for ease of manufacturing and RFI shielding.

Thermal Considerations


The transfer characteristics of the amplifier are shown in *Figure 4.* Since this is a class A input stage, power supply current increases as the input signal increases and consequently power dissipation also increases.

The CVA2422TL cannot be used without heat sinking. *Figure 2* shows the power dissipated in each channel over the operating voltage range of the device. Under white screen conditions, i.e.: 20V output, dissipation increases to 16W total. The CVA2422TL case temperature must be maintained below +90°C. If the maximum expected ambient temperature is +50°C, then a heat sink is needed with thermal resistance equal to or less than:


$$R_{th} = \frac{(90 - 50^{\circ}C)}{16W} = 2.5^{\circ}C/W$$

The CVA2422TL maximum load is 600Ω to ground or V⁺.

The output of CVA2422TL is not short circuit proof. Any resistance to V⁺ or Ground should be > 600Ω .







Information furnished by Calogic is believed to be accurate and reliable. However, no responsibility is assumed for its use: nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent rights of Calogic.