

1 K × 8 Dual-Port Static RAM

Features

- True dual-ported memory cells, which allow simultaneous reads of the same memory location
- 1 K × 8 organization
- 0.65 micron CMOS for optimum speed and power
- High speed access: 55 ns
- Low operating power: I_{CC} = 110 mA (maximum)
- Fully asynchronous operation
- Automatic power-down
- BUSY output flag on CY7C130
- INT flag for port-to-port communication
- Available in 48-pin DIP (CY7C130)

Functional Description

The CY7C130 is a high speed CMOS 1 K by 8 dual-port static RAMs. Two ports are provided permitting independent access to any location in memory. The CY7C130 can be used as a standalone 8-bit dual-port static RAM. It is the solution to applications requiring shared or buffered data, such as cache memory for DSP, bit-slice, or multiprocessor designs.

Each port <u>has</u> independent control <u>pins</u>; chip enable (\overline{CE}), write enable (\overline{RW}), <u>and</u> outp<u>ut enable</u> (\overline{OE}). Two flags are provided on each port, BUSY and INT. BUSY signals that the port is trying to access <u>the</u> same location currently being accessed by the other port. INT is an interrupt flag indicating that data is placed in a unique location (3FE for the left port and 3FF for the right port). An automatic power down feature <u>is</u> controlled independently on each port by the chip enable (\overline{CE}) pins.

The CY7C130 is available in 48-pin DIP.



Logic Block Diagram

Notes

1. CY7C130 (Master): BUSY is open drain output and requires pull-up resistor.

2. Open drain outputs: pull-up resistor required.

Cypress Semiconductor Corporation Document Number: 38-06002 Rev. *I 198 Champion Court

San Jose, CA 95134-1709 • 408-943-2600 Revised October 29, 2012



Contents

Pin Configurations	3
Pin Definitions	
Selection Guide	
Maximum Ratings	4
Operating Range	4
Electrical Characteristics	
Capacitance	5
AC Test Loads and Waveforms	
Switching Characteristics	6
Switching Waveforms	
Typical DC and AC Characteristics	

Ordering Information	. 14
Ordering Code Definitions	
Package Diagrams	. 15
Acronyms	. 16
Document Conventions	. 16
Units of Measure	. 16
Document History Page	. 17
Sales, Solutions, and Legal Information	. 18
Worldwide Sales and Design Support	. 18
Products	. 18
PSoC Solutions	. 18



Pin Configurations

Figure 1. 48-pin DIP pinout (Top View)

Pin Definitions

Left Port	Right Port	Description
CEL	CE _R	Chip enable
R/WL	R/W _R	Read/write enable
OEL	OE _R	Output enable
A _{0L} -A _{9L}	A _{0R} -A _{9R}	Address
I/O _{0L} –I/O _{7L}	I/O _{0R} –I/O _{7R}	Data bus input/output
INTL	INT _R	Interrupt flag
BUSYL	BUSYR	Busy flag
V _{CC}		Power
GND		Ground

Selection Guide

Parameter		7C130-55	Unit
Maximum access time		55	ns
Maximum operating current Commercial		110	mA
Maximum standby current	Commercial	35	mA



Maximum Ratings

Exceeding maximum ratings ^[3] may shorten the useful life of the device. User guidelines are not tested.

Storage temperature65 °C to +150 °C	С
Ambient temperature with power applied	С
Supply voltage to ground potential (pin 48 to pin 24)–0.5 V to +7.0 V	V
DC voltage applied to outputs in high Z State0.5 V to +7.0 V	V

DC input voltage	–3.5 V to +7.0 V
Output current into outputs (LOW)	20 mA
Static discharge voltage (per MIL-STD-883, method 3015)	> 2001 V
Latch-up current	> 200 mA

Operating Range

Range	Ambient Temperature	V _{CC}
Commercial	0 °C to +70 °C	5 V ± 10%

Electrical Characteristics

Over the Operating Range

Parameter [4]	Description	Description Test Conditions		7C13	7C130-55	
Falameter	Description			Min	Мах	Unit
V _{OH}	Output HIGH voltage	V _{CC} = Min, I _{OH} = -4.0 mA		2.4	-	V
V _{OL}	Output LOW voltage	I _{OL} = 4.0 mA		-	0.4	V
		I _{OL} = 16.0 mA ^[5]		-	0.5	V
V _{IH}	Input HIGH voltage			2.2	_	V
V _{IL}	Input LOW voltage			-	0.8	V
I _{IX}	Input leakage current	$GND \leq V_I \leq V_{CC}$		-5	+5	μA
I _{OZ}	Output leakage current	$GND \leq V_O \leq V_{CC}$, output disabled	d	-5	+5	μA
I _{OS}	Output short circuit current [6, 7]	V _{CC} = Max, V _{OUT} = GND		-	-350	mA
I _{CC}	V _{CC} operating supply current	$CE = V_{IL}$, outputs open, f = $f_{MAX}^{[8]}$	Commercial	-	110	mA
I _{SB1}	Standby current both ports, TTL inputs	CE_L and $CE_R \ge V_{IH}$, f = f _{MAX} ^[8]	Commercial	-	35	mA
I _{SB2}	Standby current one port, TTL inputs	$CE_L \text{ or } CE_R \ge V_{IH},$ active port outputs open, $f = f_{MAX}^{[8]}$	Commercial	-	75	mA
I _{SB3}	Standby current both ports, CMOS inputs	$\label{eq:linear_states} \begin{array}{l} \underline{Both \ ports} \\ \overline{CE}_L \ and \ \overline{CE}_R \geq V_{CC} - 0.2 \ V, \\ \overline{V}_{IN} \geq V_{CC} - 0.2 \ V \ or \ \overline{V}_{IN} \leq 0.2 \ V, \\ f = 0 \end{array}$	Commercial	-	15	mA
I _{SB4}	Standby current one port, CMOS inputs	$\begin{array}{l} \underline{One \ port} \\ \overline{CE}_L \ or \ \overline{CE}_R \geq V_{CC} - 0.2 \ V, \\ V_{IN} \geq V_{CC} - 0.2 \ V \ or \ V_{IN} \leq 0.2 \ V, \\ active \ port \ outputs \ open, \ f = f_{MAX}^{[8]} \end{array}$	Commercial	-	70	mA

Notes

- The voltage on any input or I/O pin cannot exceed the power pin during power up.
 <u>See the last page of this specification for Group A subgroup testing information.</u>
 <u>BUSY</u> and INT pins only.
 Duration of the short circuit should not exceed 30 seconds.

- 7. This parameter is guaranteed but not tested.

^{8.} At f = f_{MAX}, address and data inputs are cycling at the maximum frequency of read cycle of 1/t_{RC} and using AC Test Waveforms input levels of GND to 3 V.



Capacitance

Parameter ^[7]	Description	Test Conditions	Мах	Unit
C _{IN}	Input capacitance	T _A = 25 °C, f = 1 MHz, V _{CC} = 5.0 V	15	pF
C _{OUT}	Output capacitance		10	pF

AC Test Loads and Waveforms

Figure 2. AC Test Loads and Waveforms





Switching Characteristics

Over the Operating Range

Parameter ^[9, 10]	Description	7C1	7C130-55	
Parameter	Description		Max	– Unit
Read Cycle				
t _{RC}	Read cycle time	55	-	ns
t _{AA}	Address to data valid ^[11]	-	55	ns
t _{OHA}	Data hold from address change	0	-	ns
t _{ACE}	CE LOW to data valid ^[11]	-	55	ns
t _{DOE}	OE LOW to data valid ^[11]	-	25	ns
t _{LZOE}	OE LOW to low Z ^[12, 13, 14]	3	-	ns
t _{HZOE}	OE HIGH to high Z ^[12, 13, 14]	-	25	ns
t _{LZCE}	CE LOW to low Z [12, 13, 14]	5	-	ns
t _{HZCE}	CE HIGH to high Z ^[12, 13, 14]	-	25	ns
t _{PU}	CE LOW to power-up ^[12]	0	-	ns
t _{PD}	CE HIGH to power-down ^[12]	-	35	ns
Write Cycle [15]				
t _{WC}	Write cycle time	55	-	ns
t _{SCE}	CE LOW to write end	40	-	ns
t _{AW}	Address set-up to write end	40	-	ns
t _{HA}	Address hold from write end	2	-	ns
t _{SA}	Address set-up to write start	0	-	ns
t _{PWE}	R/W pulse width	30	-	ns
t _{SD}	Data set-up to write end	20	-	ns
t _{HD}	Data hold from write end	0	-	ns
t _{HZWE}	R/W LOW to high Z ^[14]	-	25	ns
t _{LZWE}	R/W HIGH to low Z ^[14]	0	-	ns

Notes

- 9. See the last page of this specification for Group A subgroup testing information.
- 10. Test conditions assume signal transition times of 5 ns or less, timing reference levels of 1.5 V, input pulse levels of 0 to 3.0 V and output loading of the specified I_{OI}/I_{OH} , and 30 pF load capacitance. 11. AC Test Conditions use V_{OH} = 1.6 V and V_{OL} = 1.4 V. 12. This parameter is guaranteed but not tested.

- 13. At any given temperature and voltage condition for any given device, t_{HZCE} is less than t_{LZCE} and t_{HZCE} is less than t_{LZCE}.
 14. t_{IZCE}, t_{IZWE}, t_{HZOE}, t_{IZCE} and t_{HZWE} are tested with C_L = 5<u>p</u>F as in part (b) of Figure 2 on page 5. Transition is measured ±500 mV from steady state voltage.
 15. The internal write time of the memory is defined by the overlap of CS LOW and R/W LOW. Both signals must be low to initiate a write and either signal can terminate a write by going high. The data input setup and hold timing should be referenced to the rising edge of the signal that terminates the write.



Switching Characteristics (continued)

Over the Operating Range

Parameter ^[9, 10]	Description	7C1	7C130-55	
Falameter		Min	Max	Unit
Busy/Interrupt T	iming			
t _{BLA}	BUSY LOW from address match	-	30	ns
t _{BHA}	BUSY HIGH from address mismatch ^[16]	-	30	ns
t _{BLC}	BUSY LOW from CE LOW	-	30	ns
t _{BHC}	BUSY HIGH from CE HIGH ^[16]	-	30	ns
t _{PS}	Port set-up for priority	5	-	ns
t _{WB}	R/W LOW after BUSY LOW	0	-	ns
t _{WH}	R/W HIGH after BUSY HIGH	35	-	ns
t _{BDD}	BUSY HIGH to valid data	-	45	ns
t _{DDD}	Write data valid to read data valid	-	Note 17	ns
t _{WDD}	Write pulse to data delay	-	Note 17	ns
Interrupt Timing				-
t _{WINS}	R/W to INTERRUPT set time	-	45	ns
t _{EINS}	CE to INTERRUPT set time	-	45	ns
t _{INS}	Address to INTERRUPT set time	-	45	ns
t _{OINR}	OE to INTERRUPT reset time ^[18]	-	45	ns
t _{EINR}	CE to INTERRUPT reset time ^[18]	_	45	ns
t _{INR}	Address to INTERRUPT reset time [18]	-	45	ns

Notes
16. These parameters are measured from the input signal changing, until the output pin goes to a high-impedance state.
17. <u>A write</u> operation on Port A, where Port A has priority, leaves the data on Port B's outputs undisturbed until one access time after one of the following: BUSY on Port B goes HIGH.
Port B's address is toggled.
CE for Port B is toggled.
R/W for Port B is toggled during valid read.
18. t_{LZCE}, t_{LZWE}, t_{HZOE}, t_{LZOE}, t_{HZCE} and t_{HZWE} are tested with C_L = 5 pF as in part (b) of Figure 2 on page 5. Transition is measured ±500 mV from steady state voltage.



Switching Waveforms



Notes19. R/W is HIGH for read cycle.20. Device is continuously selected, $\overline{CE} = V_{IL}$ and $\overline{OE} = V_{IL}$.21. Address valid prior to or coincident with CE transition LOW.





Figure 6. Write Cycle No. 1 (OE Three-States Data I/Os – Either Port [22, 23]

Notes

DATA_{OUT}

^{22.} The internal write time of the memory is defined by the overlap of CS LOW and R/W LOW. Both signals must be low to initiate a write and either signal can terminate a write by going high. The data input setup and hold timing should be referenced to the rising edge of the signal that terminates the write.

^{23.} If \overline{OE} is LOW during a R/W controlled write cycle, the write pulse width must be the larger of t_{PWE} or $t_{HZWE} + t_{SD}$ to allow the data I/O pins to enter high impedance and for data to be placed on the bus for the required t_{SD} . 24. These parameters are measured from the input signal changing, until the output pin goes to a high-impedance state. 25. If the \overline{CE} LOW transition occurs simultaneously with or after the R/W LOW transition, the outputs remain in the high impedance state.

















Typical DC and AC Characteristics





Ordering Information

Speed (ns)	Ordering Code	Package Name	Package Type	Operating Range
55	CY7C130-55PC	P25	48-pin (600 Mil) Molded DIP	Commercial

Ordering Code Definitions





Package Diagrams

<u>0.090</u> 0.110



<u>0.014</u> 0.022

Figure 12. 48-pin PDIP (2.460 × 0.550 × 0.170 inches) P48.6 Package Outline, 51-85020

51-85020 *D



Acronyms

Acronym	Description		
CE	chip enable		
CMOS	complementary metal oxide semiconductor		
DIP	dual in-line package		
I/O	input/output		
OE	output enable		
PDIP	plastic dual in-line package		
SRAM	static random access memory		
TTL	transistor-transistor logic		

Document Conventions

Units of Measure

Symbol	Unit of Measure	
°C	degree Celsius	
MHz	megahertz	
μA	microampere	
mA	milliampere	
ms	millisecond	
mV	millivolt	
ns	nanosecond	
pF	picofarad	
V	volt	
W	watt	



Document History Page

Rev.	ECN No.	Orig. of Change	Submission Date	Description of Change
**	110169	SZV	09/29/01	Change from Spec number: 38-00027 to 38-06002
*A	122255	RBI	12/26/02	Power up requirements added to Maximum Ratings Information
*B	236751	YDT	See ECN	Removed cross information from features section
*C	325936	RUY	See ECN	Added pin definitions table, 52-pin PQFP package diagram and Pb-free info mation
*D	393153	YIM	See ECN	Added CY7C131-15JI to ordering information Added Pb-Free parts to ordering information: CY7C131-15JXI
*E	2623540	VKN/PYRS	12/17/08	Added CY7C130A and CY7C131A parts Removed military information Updated ordering information.
*F	2897217	RAME	03/22/2010	Updated Ordering Information. Updated Package Diagrams.
*G	3054633	ADMU	10/11/2010	Updated Ordering Information and added Ordering Code Definitions. Updated Package Diagrams. Added Acronyms and Units of Measure. Minor edits and updated in new template.
*H	3402163	ADMU	10/12/2011	Removed pruned part CY7C131-25NC from Ordering Information Updated Package Diagrams.
*	3796621	SMCH	10/29/2012	Updated Features (Removed CY7C130A, CY7C131, CY7C131A related information; removed 52-pin PLCC, 52-pin TQFP package related information). Updated Functional Description (Removed CY7C130A, CY7C131, CY7C131, related information; removed 52-pin PLCC, 52-pin TQFP package related information). Updated Pin Configurations (Removed 52-pin PLCC, 52-pin TQFP package related information). Updated Selection Guide (Removed CY7C130A, CY7C131, CY7C131A related information; removed 15 ns, 25 ns, 30 ns, 35 ns, 45 ns speed bins information, removed Industrial temperature range information). Updated Operating Range (Removed Industrial temperature range and Militar temperature range information). Updated Electrical Characteristics (Removed CY7C130A, CY7C131, CY7C131A related information; removed 15 ns, 25 ns, 30 ns, 35 ns, 45 ns speed bins information). Updated Switching Characteristics (Removed CY7C130A, CY7C131, CY7C131A related information; removed 15 ns, 25 ns, 30 ns speed bins information). Updated Switching Characteristics (Removed CY7C130A, CY7C131, CY7C131A related information; removed 15 ns, 25 ns, 30 ns speed bins information). Updated Switching Characteristics (Removed CY7C130A, CY7C131, CY7C131A related information; removed 35 ns, 45 ns speed bins information Updated Ordering Information; removed 35 ns, 45 ns speed bins informatior Updated Ordering Information; removed 35 ns, 45 ns speed bins informatior Updated Package Diagrams (Removed 52-pin PLCC, 52-pin TQFP package related information).



Sales, Solutions, and Legal Information

Worldwide Sales and Design Support

Cypress maintains a worldwide network of offices, solution centers, manufacturer's representatives, and distributors. To find the office closest to you, visit us at Cypress Locations.

Products

Automotive	cypress.com/go/automotive
Clocks & Buffers	cypress.com/go/clocks
Interface	cypress.com/go/interface
Lighting & Power Control	cypress.com/go/powerpsoc
	cypress.com/go/plc
Memory	cypress.com/go/memory
Optical & Image Sensing	cypress.com/go/image
PSoC	cypress.com/go/psoc
Touch Sensing	cypress.com/go/touch
USB Controllers	cypress.com/go/USB
Wireless/RF	cypress.com/go/wireless

PSoC Solutions

psoc.cypress.com/solutions PSoC 1 | PSoC 3 | PSoC 5

© Cypress Semiconductor Corporation, 2001-2012. The information contained herein is subject to change without notice. Cypress Semiconductor Corporation assumes no responsibility for the use of any circuitry other than circuitry embodied in a Cypress product. Nor does it convey or imply any license under patent or other rights. Cypress products are not warranted nor intended to be used for medical, life support, life saving, critical control or safety applications, unless pursuant to an express written agreement with Cypress. Furthermore, Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress products in life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Any Source Code (software and/or firmware) is owned by Cypress Semiconductor Corporation (Cypress) and is protected by and subject to worldwide patent protection (United States and foreign), United States copyright laws and international treaty provisions. Cypress hereby grants to licensee a personal, non-exclusive, non-transferable license to copy, use, modify, create derivative works of, and compile the Cypress Source Code and derivative works for the sole purpose of creating custom software and or firmware in support of licensee product to be used only in conjunction with a Cypress integrated circuit as specified in the applicable agreement. Any reproduction, modification, translation, compilation, or representation of this Source Code except as specified above is prohibited without the express written permission of Cypress.

Disclaimer: CYPRESS MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Cypress reserves the right to make changes without further notice to the materials described herein. Cypress does not assume any liability arising out of the application or use of any product or circuit described herein. Cypress does not authorize its products for use as critical components in life-support systems where a malfunction or failure may reasonably be expected to result in significant injury to the user. The inclusion of Cypress' product in a life-support systems application implies that the manufacturer assumes all risk of such use and in doing so indemnifies Cypress against all charges.

Use may be limited by and subject to the applicable Cypress software license agreement.

Document Number: 38-06002 Rev. *I

Revised October 29, 2012

All products and company names mentioned in this document may be the trademarks of their respective holders.