

LM319


Dual Comparator

Features


- Operates From a Single 5V Supply
- Typically 80ns Response Time at $\pm 15V$
- Open Collector Outputs : up to $+35V$
- High Output Drive Current : 25mA
- Inputs and Outputs can be Isolated From System Ground
- Minimum Fan-Out of 2 (Each Side)
- Two Independent Comparators

Description


The LM319 is a dual high speed voltage comparator designed to operate from a single +5V supply up to $\pm 15V$ dual supplies. Open collector of the output stage makes the LM319 compatible with RTL, DTL and TTL as well as capable of driving lamps and relays at currents up to 25mA. Typical response time of 80ns with $\pm 15V$ power supplies makes the LM319 ideal for application in fast A/D converts, level shiftier, oscillators, and multivibrators.



Internal Block Diagram



Schematic Diagram



Absolute Maximum Ratings

Parameter	Symbol	Value	Unit
Supply Voltage	V _{CC}	36	V
Output to Negative Supply Voltage	V _O - V _{EE}	36	V
Ground to Negative Supply Voltage	V _{EE}	25	V
Ground to Positive Supply Voltage	V _{CC}	18	V
Differential Input Voltage	V _{I(DIFF)}	5	V
Input Voltage	V _I	±15	V
Output Short Circuit Duration	-	10	sec
Power Dissipation	P _D	500	mW
Thermal Resistance Junction-Ambient Max.	R _{θja}	250	°C/W
Operating Temperature Range	T _{OPR}	0 ~ +70	°C
Storage Temperature Range	T _{STG}	-65 ~ +150	°C

Electrical Characteristics

(V_{CC} = +15V, V_{EE} = -15V, T_A = 25°C, unless otherwise specified)

Parameter	Symbol	Conditions	LM319			Unit
			Min.	Typ.	Max.	
Input Offset Voltage (Note1)	V _{IO}	R _S ≤ 5kΩ Note3	-	2.0	8.0	mV
Input Offset Current (Note1)	I _{IO}		-	10	200	nA
Input Bias Current	I _{BIAS}		-	150	1000	nA
Voltage Gain	G _V	-	8	40	-	V/mV
Response Time (Note2)	T _{RES}	V _{CC} = ±15V	-	80	-	ns
Saturation Voltage	V _{SAT}	V _{CC} =15V, V _{EE} = -15V, V _I ≤ -5mV, I _O = 25mA	-	0.6	1.5	V
		V _{CC} = 4.5V, V _{EE} = 0V V _I ≤ -10mV, I _O ≤ 3.2mA	Note3	-	0.3	0.4
Output Leakage Current	I _{O(LKG)}	V _I ≥ 5mV, V _{O(P)} = 35V		-	-	μA
		V _I ≥ 10mV, V _{O(P)} = 35V	Note3	-	0.2	10
Input Voltage Range	V _{I(R)}	Note3	V _{CC} = ±15V	-	±13	V
			V _{CC} = 5V, V _{EE} = 0V	1	-	3
Differential Input Voltage	V _{I(DIFF)}	-	-	-	±5	V
Positive Supply Current	I _{CC1}	V _{CC} = 5V, V _{EE} = 0V	-	3.6	-	mA
Positive Supply Current	I _{CC2}	V _{CC} = ±15V	-	7.5	12.5	mA
Negative Supply Current	I _{EE}	V _{CC} = ±15V	-	3	5	mA

Notes :

1. The offset voltage and offset currents given are the maximum values required to drive the output within a volt of either supply with a 1mA load. Thus, these parameters define an error band and take into account the worst case effects of voltage gain and input impedance.
2. The response time specified is for a 100mV input step with 5mV overdrive.
3. LM319 : 0 ≤ T_A ≤ +70°C

Typical Performance Characteristics




Figure 1. Input Current




Figure 2. Output Saturation Voltage




Figure 3. Transfer Function




Figure 4. Response Time for Various Input Overdriver




Figure 5. Response Time Various Input Overdriver




Figure 6. Input Characteristics

Typical Performance Characteristics (Continued)




Figure 7. Response Time for Various Input Overdriver




Figure 8. Response Time for Various Input Overdriver




Figure 9. Supply Current




Figure 10. Supply Current




Figure 11. Common Mode Limits





Figure 12. Output Limiting Characteristics

Mechanical Dimensions

Package

Dimensions in millimeters

14-DIP




Mechanical Dimensions (Continued)

Package

Dimensions in millimeters

14-SOP



Ordering Information

Product Number	Package	Operating Temperature
LM319N	14-DIP	0 ~ +70°C
LM319M	14-SOP	

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.