- 2-V to 5.5-V V_{CC} Operation
- Max t_{pd} of 6.5 ns at 5 V
- Typical V_{OLP} (Output Ground Bounce)
 <0.8 V at V_{CC} = 3.3 V, T_A = 25°C
- Typical V_{OHV} (Output V_{OH} Undershoot)
 >2.3 V at V_{CC} = 3.3 V, T_A = 25°C
- Outputs Are Disabled During Power Up and Power Down With Inputs Tied to GND
- Support Mixed-Mode Voltage Operation on All Ports
- Latch-Up Performance Exceeds 100 mA Per JESD 78, Class II
- ESD Protection Exceeds JESD 22
 - 2000-V Human-Body Model (A114-A)
 - 200-V Machine Model (A115-A)
 - 1000-V Charged-Device Model (C101)


description/ordering information

These hex inverter buffers/drivers are designed for 2-V to 5.5-V V_{CC} operation.


The 'LV06A devices perform the Boolean function $Y = \overline{A}$ in positive logic.

The open-drain outputs require pullup resistors to perform correctly and can be connected to other open-drain outputs to implement active-low wired-OR or active-high wired-AND functions.

SN54LV06A . . . J OR W PACKAGE SN74LV06A . . . D, DB, DGV, NS, OR PW PACKAGE (TOP VIEW)



SN54LV06A . . . FK PACKAGE (TOP VIEW)



NC - No internal connection

These devices are fully specified for partial-power-down applications using I_{off}. The I_{off} circuitry disables the outputs, preventing damaging current backflow through the devices when they are powered down.

ORDERING INFORMATION

| TA | PACKA | _{GE} † | ORDERABLE PART NUMBER | TOP-SIDE MARKING |
|----------------|-------------|-----------------|--------------------------|---------------------|
| | SOIC - D | Tube of 50 | SN74LV06AD | 11/004 |
| | 201C - D | Reel of 2500 | SN74LV06ADR | LV06A |
| | SOP – NS | Reel of 2000 | SN74LV06ANSR | 74LV06A |
| 4000 1- 0500 | SSOP – DB | Reel of 2000 | SN74LV06ADBR | LV06A |
| –40°C to 85°C | | Tube of 90 | SN74LV06APW | |
| | TSSOP - PW | Reel of 2000 | SN74LV06APWR | LV06A |
| | | Reel of 250 | SN74LV06APWT | |
| | TVSOP – DGV | Reel of 2000 | SN74LV06ADGVR | LV06A |
| | CDIP – J | Tube of 25 | SNJ54LV06AJ | SNJ54LV06AJ |
| −55°C to 125°C | CFP – W | Tube of 150 | SNJ54LV06AW | SNJ54LV06AW |
| | LCCC - FK | Tube of 55 | SNJ54LV06AFK | SNJ54LV06AFK |

[†] Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at www.ti.com/sc/package.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



FUNCTION TABLE (each buffer/driver)

| INPUT A | OUTPUT Y |
|------------|-------------|
| Н | L |
| L | Н |

logic diagram, each inverter (positive logic)



absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

| Supply voltage range, V _{CC} Input voltage range, V _I (see Note 1)Voltage range applied to any output in the high | | |
|---|-------------|----------------|
| (see Note 1) | | –0.5 V to 7 V |
| Input clamp current, I _{IK} (V _I < 0) | | –20 mA |
| Output clamp current, I _{OK} (V _O < 0) | | –50 mA |
| Continuous output current, I_O ($V_O = 0$ to V_{CC}) | | –35 mA |
| Continuous current through V _{CC} or GND | | ±50 mA |
| Package thermal impedance, θ _{JA} (see Note 3): | : D package | 86°C/W |
| | DB package | 96°C/W |
| | DGV package | 127°C/W |
| | NS package | 76°C/W |
| | PW package | |
| Storage temperature range, T _{stg} | | –65°C to 150°C |

[†] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

- 2. This value is limited to 5.5 V maximum.
- 3. The package thermal impedance is calculated in accordance with JESD 51-7.



NOTES: 1. The input and output negative-voltage ratings may be exceeded if the input and output current ratings are observed.

recommended operating conditions (see Note 4)

| | | | SN54L\ | /06A | SN74LV | /06A | |
|-----------------|------------------------------------|--|-----------------------|----------|---------------------|----------|------|
| | | | MIN | MAX | MIN | MAX | UNIT |
| VCC | Supply voltage | | 2 | 5.5 | 2 | 5.5 | V |
| | | V _{CC} = 2 V | 1.5 | | 1.5 | | |
| \ <i>I</i> | High lovel input valtage | $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ | V _{CC} × 0.7 | | $V_{CC} \times 0.7$ | | V |
| V_{IH} | High-level input voltage | $V_{CC} = 3 V \text{ to } 3.6 V$ | $V_{CC} \times 0.7$ | | $V_{CC} \times 0.7$ | | V |
| | | $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ | $V_{CC} \times 0.7$ | | $V_{CC} \times 0.7$ | | |
| | | V _{CC} = 2 V | | 0.5 | | 0.5 | |
| ., | Laur laural import violitaire | $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ | V | CC × 0.3 | V | CC × 0.3 | V |
| V_{IL} | Low-level input voltage | V _{CC} = 3 V to 3.6 V | V | CC × 0.3 | V ₍ | CC × 0.3 | V |
| | | V _{CC} = 4.5 V to 5.5 V | V | CC × 0.3 | V ₍ | CC × 0.3 | |
| ٧ _I | Input voltage | | 0 | 5.5 | 0 | 5.5 | V |
| VO | Output voltage | | 0 6 | 5.5 | 0 | 5.5 | V |
| | | V _{CC} = 2 V | 20 | 50 | | 50 | μΑ |
| 1 | Lave lavel autout aumant | $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ | 000 | 2 | | 2 | |
| IOL | Low-level output current | V _{CC} = 3 V to 3.6 V | 7 | 8 | | 8 | mA |
| | | $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ | | 16 | | 16 | |
| | | $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ | | 200 | | 200 | |
| Δt/Δν | Input transition rise or fall rate | $V_{CC} = 3 V \text{ to } 3.6 V$ | | 100 | | 100 | ns/V |
| | | V _{CC} = 4.5 V to 5.5 V | | 20 | | 20 | |
| TA | Operating free-air temperature | <u> </u> | -55 | 125 | -40 | 85 | °C |

NOTE 4: All unused inputs of the device must be held at V_{CC} or GND to ensure proper device operation. Refer to the TI application report, Implications of Slow or Floating CMOS Inputs, literature number SCBA004.

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

| 24244555 | TEST SOUR | | ., | SN | 54LV06 | Α | SN | 74LV06 | Α | |
|------------------|-------------------------------|-----------|--------------|-----|--------|------|-----|--------|------|------|
| PARAMETER | TEST CONDIT | IIONS | vcc | MIN | TYP | MAX | MIN | TYP | MAX | UNIT |
| | I _{OL} = 50 μA | | 2 V to 5.5 V | | | 0.1 | | | 0.1 | |
| | $I_{OL} = 2 \text{ mA}$ | | 2.3 V | | 12/ | 0.4 | | | 0.4 | ., |
| VOL | I _{OL} = 8 mA | | 3 V | | ZEL | 0.44 | | | 0.44 | V |
| | I _{OL} = 16 mA | | 4.5 V | | 2 | 0.55 | | | 0.55 | |
| lį | V _I = 5.5 V or GND | | 0 to 5.5 V | *, | 5 | ±1 | | | ±1 | μΑ |
| ЮН | $V_{I} = V_{IL}$ | VOH = VCC | 5.5 V | 90 | Ĭ | ±2.5 | | | ±2.5 | μΑ |
| Icc | $V_I = V_{CC}$ or GND, | IO = 0 | 5.5 V | bo | | 20 | | | 20 | μΑ |
| l _{off} | V_I or $V_O = 0$ to 5.5 V | | 0 | | | 5 | | | 5 | μΑ |
| C _i | $V_I = V_{CC}$ or GND | | 3.3 V | | 1.6 | | | 1.6 | | pF |

SN54LV06A, SN74LV06A HEX INVERTER BUFFERS/DRIVERS WITH OPEN-DRAIN OUTPUTS

SCES336H - MAY 2000 - REVISED APRIL 2005

switching characteristics over recommended operating free-air temperature range, V_{CC} = 2.5 V \pm 0.2 V (unless otherwise noted) (see Figure 1)

| DADAMETER | FROM | то | LOAD | T, | λ = 25°C | ; | SN54L | V06A | SN74L | V06A | |
|------------------|---------|----------|------------------------|-----|----------|-------|-------|------|-------|------|------|
| PARAMETER | (INPUT) | (OUTPUT) | CAPACITANCE | MIN | TYP | MAX | MIN | MAX | MIN | MAX | UNIT |
| ^t PLH | | V | 0 45 -5 | | 5.4* | 10.4* | 1* | 13* | 1 | 13 | |
| t _{PHL} | А | Y | $C_L = 15 pF$ | | 7.2* | 10.4* | 1*0 | 13* | 1 | 13 | ns |
| t _{PLH} | ^ | V | C: _ 50 pF | | 9.7 | 15.2 | 0.0 | 18 | 1 | 18 | 20 |
| t _{PHL} | A | , i | C _L = 50 pF | | 9.3 | 15.2 | 1 | 18 | 1 | 18 | ns |

^{*} On products compliant to MIL-PRF-38535, this parameter is not production tested.

switching characteristics over recommended operating free-air temperature range, V_{CC} = 3.3 V \pm 0.3 V (unless otherwise noted) (see Figure 1)

| DADAMETER | FROM | то | LOAD | T, | 4 = 25°C | ; | SN54L\ | √06A | SN74L | V06A | |
|------------------|---------|-------------|------------------------|-----|----------|------|--------|------|-------|------|------|
| PARAMETER | (INPUT) | (OUTPUT) | CAPACITANCE | MIN | TYP | MAX | MIN | MAX | MIN | MAX | UNIT |
| ^t PLH | | > | 0 455 | | 4.1* | 7.1* | 1* | 8.5* | 1 | 8.5 | |
| ^t PHL | А | Y | C _L = 15 pF | | 4.9* | 7.1* | 1*0 | 8.5* | 1 | 8.5 | ns |
| ^t PLH | ^ | ~ | C _I = 50 pF | | 7.1 | 10.6 | 1. | 12 | 1 | 12 | 20 |
| ^t PHL | А | T | CL = 50 pr | | 6.4 | 10.6 | 1 | 12 | 1 | 12 | ns |

^{*} On products compliant to MIL-PRF-38535, this parameter is not production tested.

switching characteristics over recommended operating free-air temperature range, V_{CC} = 5 V \pm 0.5 V (unless otherwise noted) (see Figure 1)

| DADAMETED | FROM | то | LOAD | T, | չ = 25°C | ; | SN54L | √06A | SN74L | .V06A | LINUT |
|------------------|---------|----------|------------------------|-----|----------|------|-------|------|-------|-------|-------|
| PARAMETER | (INPUT) | (OUTPUT) | CAPACITANCE | MIN | TYP | MAX | MIN | MAX | MIN | MAX | UNIT |
| ^t PLH | • | V | 0. 45 = 5 | | 3* | 5.5* | 1* | 6.5* | 1 | 6.5 | |
| tPHL | А | Y | C _L = 15 pF | | 3.3* | 5.5* | 1*0 | 6.5* | 1 | 6.5 | ns |
| ^t PLH | ^ | ~ | C: 50 pF | | 4.8 | 7.5 | 6/1/ | 8.5 | 1 | 8.5 | |
| ^t PHL | А | r | C _L = 50 pF | | 4.4 | 7.5 | 1 | 8.5 | 1 | 8.5 | ns |

^{*} On products compliant to MIL-PRF-38535, this parameter is not production tested.

noise characteristics, $V_{CC} = 3.3 \text{ V}$, $C_L = 50 \text{ pF}$, $T_A = 25^{\circ}\text{C}$ (see Note 5)

| | DADAMETED | SN | 74LV06 | Α | |
|--------------------|---|------|--------|------|------|
| | PARAMETER | MIN | TYP | MAX | UNIT |
| V _{OL(P)} | Quiet output, maximum dynamic VOL | | 0.5 | 8.0 | V |
| V _{OL(V)} | Quiet output, minimum dynamic V _{OL} | | -0.1 | -0.8 | V |
| VOH(V) | Quiet output, minimum dynamic VOH | | 3.3 | | V |
| VIH(D) | High-level dynamic input voltage | 2.31 | | | V |
| V _{IL(D)} | Low-level dynamic input voltage | | | 0.99 | V |

NOTE 5: Characteristics are for surface-mount packages only.


operating characteristics, $T_A = 25^{\circ}C$

| | | PARAMETER | TEST CO | NDITIONS | VCC | TYP | UNIT |
|---|----------|-------------------------------|------------------------|------------|-------|-----|------|
| ſ | <u> </u> | Down discipation conscitance | C. 50 pF | f = 10 MHz | 3.3 V | 2.6 | pF |
| ı | Cpd | Power dissipation capacitance | $C_L = 50 \text{ pF},$ | I = 10 MHZ | 5 V | 4.7 | рг |

PRODUCT PREVIEW information concerns products in the formative or design phase of development. Characteristic data and other specifications are design goals. Texas Instruments reserves the right to change or discontinue these products without notice.



PARAMETER MEASUREMENT INFORMATION



NOTES: A. C_L includes probe and jig capacitance.

- B. All input pulses are supplied by generators having the following characteristics: PRR \leq 1 MHz, $Z_O = 50 \Omega$, $t_f \leq 3$ ns. $t_f \leq 3$ ns.
- C. The outputs are measured one at a time, with one input transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms





zti.com 24-Jan-2013

PACKAGING INFORMATION

| Orderable Device | Status | Package Type | Package Drawing | Pins | Package Qty | Eco Plan | Lead/Ball Finish | MSL Peak Temp | Op Temp (°C) | Top-Side Markings | Samples |
|------------------|--------|--------------|--------------------|------|-------------|----------------------------|------------------|--------------------|--------------|-------------------|---------|
| SN74LV06AD | ACTIVE | SOIC | D | 14 | 50 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADBR | ACTIVE | SSOP | DB | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADBRE4 | ACTIVE | SSOP | DB | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADBRG4 | ACTIVE | SSOP | DB | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADE4 | ACTIVE | SOIC | D | 14 | 50 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADG4 | ACTIVE | SOIC | D | 14 | 50 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADGVR | ACTIVE | TVSOP | DGV | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADGVRE4 | ACTIVE | TVSOP | DGV | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADGVRG4 | ACTIVE | TVSOP | DGV | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADR | ACTIVE | SOIC | D | 14 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADRE4 | ACTIVE | SOIC | D | 14 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ADRG4 | ACTIVE | SOIC | D | 14 | 2500 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06ANSR | ACTIVE | so | NS | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | 74LV06A | Samples |
| SN74LV06ANSRE4 | ACTIVE | so | NS | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | 74LV06A | Samples |
| SN74LV06ANSRG4 | ACTIVE | so | NS | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | 74LV06A | Samples |
| SN74LV06APW | ACTIVE | TSSOP | PW | 14 | 90 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWE4 | ACTIVE | TSSOP | PW | 14 | 90 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |





www.ti.com 24-Jan-2013

| Orderable Device | Status | Package Type | _ | Pins | Package Qty | Eco Plan | Lead/Ball Finish | MSL Peak Temp | Op Temp (°C) | Top-Side Markings | Samples |
|------------------|--------|--------------|---------|------|-------------|----------------------------|------------------|--------------------|--------------|-------------------|---------|
| | (1) | | Drawing | | | (2) | | (3) | | (4) | |
| SN74LV06APWG4 | ACTIVE | TSSOP | PW | 14 | 90 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWR | ACTIVE | TSSOP | PW | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWRE4 | ACTIVE | TSSOP | PW | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWRG4 | ACTIVE | TSSOP | PW | 14 | 2000 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWT | ACTIVE | TSSOP | PW | 14 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWTE4 | ACTIVE | TSSOP | PW | 14 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |
| SN74LV06APWTG4 | ACTIVE | TSSOP | PW | 14 | 250 | Green (RoHS & no Sb/Br) | CU NIPDAU | Level-1-260C-UNLIM | -40 to 85 | LV06A | Samples |

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and

⁽⁴⁾ Only one of markings shown within the brackets will appear on the physical device.



PACKAGE OPTION ADDENDUM

24-Jan-2013

continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

PACKAGE MATERIALS INFORMATION

www.ti.com 26-Jan-2013


TAPE AND REEL INFORMATION





| Α0 | Dimension designed to accommodate the component width |
|----|---|
| | Dimension designed to accommodate the component length |
| K0 | Dimension designed to accommodate the component thickness |
| W | Overall width of the carrier tape |
| P1 | Pitch between successive cavity centers |

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

| Device | Package Type | Package Drawing | | SPQ | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|---------------|-----------------|--------------------|----|------|--------------------------|--------------------------|------------|------------|------------|------------|-----------|------------------|
| SN74LV06ADBR | SSOP | DB | 14 | 2000 | 330.0 | 16.4 | 8.2 | 6.6 | 2.5 | 12.0 | 16.0 | Q1 |
| SN74LV06ADGVR | TVSOP | DGV | 14 | 2000 | 330.0 | 12.4 | 6.8 | 4.0 | 1.6 | 8.0 | 12.0 | Q1 |
| SN74LV06ADR | SOIC | D | 14 | 2500 | 330.0 | 16.4 | 6.5 | 9.0 | 2.1 | 8.0 | 16.0 | Q1 |
| SN74LV06ANSR | SO | NS | 14 | 2000 | 330.0 | 16.4 | 8.2 | 10.5 | 2.5 | 12.0 | 16.0 | Q1 |
| SN74LV06APWR | TSSOP | PW | 14 | 2000 | 330.0 | 12.4 | 6.9 | 5.6 | 1.6 | 8.0 | 12.0 | Q1 |
| SN74LV06APWT | TSSOP | PW | 14 | 250 | 330.0 | 12.4 | 6.9 | 5.6 | 1.6 | 8.0 | 12.0 | Q1 |

www.ti.com 26-Jan-2013



*All dimensions are nominal

| Device | Package Type | Package Drawing | Pins | SPQ | Length (mm) | Width (mm) | Height (mm) |
|---------------|--------------|-----------------|------|------|-------------|------------|-------------|
| SN74LV06ADBR | SSOP | DB | 14 | 2000 | 367.0 | 367.0 | 38.0 |
| SN74LV06ADGVR | TVSOP | DGV | 14 | 2000 | 367.0 | 367.0 | 35.0 |
| SN74LV06ADR | SOIC | D | 14 | 2500 | 367.0 | 367.0 | 38.0 |
| SN74LV06ANSR | SO | NS | 14 | 2000 | 367.0 | 367.0 | 38.0 |
| SN74LV06APWR | TSSOP | PW | 14 | 2000 | 367.0 | 367.0 | 35.0 |
| SN74LV06APWT | TSSOP | PW | 14 | 250 | 367.0 | 367.0 | 35.0 |

DGV (R-PDSO-G**)

24 PINS SHOWN

PLASTIC SMALL-OUTLINE



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15 per side.

D. Falls within JEDEC: 24/48 Pins – MO-153 14/16/20/56 Pins – MO-194



D (R-PDSO-G14)

PLASTIC SMALL OUTLINE



- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
- Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
- E. Reference JEDEC MS-012 variation AB.



D (R-PDSO-G14)

PLASTIC SMALL OUTLINE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Publication IPC-7351 is recommended for alternate designs.
- D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
- E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.



PW (R-PDSO-G14)

PLASTIC SMALL OUTLINE




- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M—1994.
- B. This drawing is subject to change without notice.
- Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
- Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
- E. Falls within JEDEC MO-153



PW (R-PDSO-G14)

PLASTIC SMALL OUTLINE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Publication IPC-7351 is recommended for alternate designs.
- D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
- E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.



MECHANICAL DATA

NS (R-PDSO-G**)

14-PINS SHOWN

PLASTIC SMALL-OUTLINE PACKAGE



- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15.



DB (R-PDSO-G**)

PLASTIC SMALL-OUTLINE

28 PINS SHOWN



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.

D. Falls within JEDEC MO-150

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have *not* been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products Applications

Audio www.ti.com/audio Automotive and Transportation www.ti.com/automotive Communications and Telecom **Amplifiers** amplifier.ti.com www.ti.com/communications **Data Converters** dataconverter.ti.com Computers and Peripherals www.ti.com/computers **DLP® Products** www.dlp.com Consumer Electronics www.ti.com/consumer-apps

DSP **Energy and Lighting** dsp.ti.com www.ti.com/energy Clocks and Timers www.ti.com/clocks Industrial www.ti.com/industrial Interface interface.ti.com Medical www.ti.com/medical logic.ti.com Logic Security www.ti.com/security

Power Mgmt power.ti.com Space, Avionics and Defense www.ti.com/space-avionics-defense

Microcontrollers <u>microcontroller.ti.com</u> Video and Imaging <u>www.ti.com/video</u>

RFID www.ti-rfid.com

OMAP Applications Processors www.ti.com/omap TI E2E Community e2e.ti.com

Wireless Connectivity <u>www.ti.com/wirelessconnectivity</u>